

Hera RSND

- Indoor Sounder Type: A
- One tone
- Easy for installation



DESCRIPTION

Hera RSND is a conventional fire alarm sounder with one input for connection to a conventional fire alarm panel. Hera RSND is designed for indoor use only. The sounder is easy for installation and consists of three parts: mounting plane basis, sounder body and a plastic red cover.

FEATURES

- 1 tone
- High sound level- High (102dB)
- Small and compact design
- Certified according to standard EN54 – part 3

TECHNICAL SPECIFICATIONS

- Operating Voltage Range20-28VDC
- Maximal consumption.....55mA @ 24VDC
- Maximal sound volume.....102dB @ 1m
- Color.....Red/White
- Material.....ABS
- Dimensions.....102x32mm

COMPATIBLE PRODUCT RANGE

- MAG 2/4/8/8 Plus** - Conventional Fire Alarm Panels
- SensorIS MOUT** - Potential output for conventional sounders
- IRIS/SIMPO** - Addressable fire alarm panels

PACKING INFORMATION

- Packing box** - 1 unit Hera RSND, dimensions 108/108/48 mm.
- Carton box** - 100 units Hera RSND, dimensions 560/362/230 mm.

Last update: 12.2020